



burkert









A rotork Brand

Fine Controls have been supplying process controls & instrumentation equipment since 1994, & now serves an ever expanding customer base, both in the UK & globally.

We offer a full range of valve & instrumentation products & services, with our product rangerepresenting leading technologies & brands:

Flow: Flow Meters & Transmitters, Flow Switches, Flow Control Valves & Batch Control Systems

Temperature: Temperature Probes & Thermowells, Temperature ransmitters, Temperature Regulators & Temperature Displays

Level: Level Transmitters & Switches

Pressure: Pressure Gauges & Transmitters, Precision & High Pressure Regulators & I-P Converters, Volume boosters.

Precision Pneumatics: Pressure Regulators, I-P Converters, Volume Boosters, Vacuum Regulators

Valves: Solenoid & Pneumatic Valves, Control Valves & Positioners, Actuated Ball, Globe or Diaphragm Valves & Isolation Valves

Services: Repair, Calibration, Panel Build, System Design & Commissioning



A rotorik Brand



Honeywell



Baumer Group









Fine Controls (UK) LTD, Bassendale Road, Croft Business Park, Bromborough, Wirral, CH62 3QL UK Tel: 0151 343 9966 Email: sales@finecontrols.com





multiCELL -**Multifunction Transmitter/Controller**

- Compatible with most common flow, pH/O.R.P. and conductivity sensors, directly connected
- Simple, intuitive user interface supported by a large adjustable backlit display (4 user defined views)
- Basic transmitter/controller with hardware extension possibilities (up to 6 free slots)
- Functionality extendable by software options
- Data logging









Type 7800 Dosing pump

Type 8201 pH sensor

Type 8200

Probes holder

The 8619 multifunction transmitter/controller is a microprocessor transmitter/controller for connection of sensors which deliver raw signals for pH, O.R.P. and conductivity and flow via pulses. Type 8619 is the ideal device for measurement and control and as well dosing processes e.g. in applications of water treatment plants (like boiler, cooling tower or reverse osmosis systems) and food and pharma plants.

Modularity in hardware and software offer high flexibility for adjusting it to the applications resulting in having a very good price to functionality relation.

Sophisticated electronics and state of the art control algorithms ensure that optimum process control is maintained at all times with minimal operator intervention so achieving highest quality.

Type 8220 Type 8221 Conductivity sensor 4-pole technology 2-pole technology

Type 8030 INLINE flow sensor

Type 8802 Process control valve

Technical data				
General data				
Mounting	panel mount unit for 92 x 92 mm cutout			
Materials Housing, fastening element / Seal Cover, vision panel / Overlay Backplate / Screws Plug-in connector / Pin	PPO / Silicone PC / Silicone rubber Stainless steel 304 / Stainless steel A4 PBT / Copper alloy gold-plated			
Display	LC graphic display, light blue backlighted; 128x168 pix- els resolution; German, English, French languages			
Keypad	4 soft keys [F1] [F2] [F3] [F4] for dynamic functions 1 central navigation key with [♠] [♠] [♣] [♣] assign- ments			
Logbook	Data logger of up to 16 values			
Sensor monitor	Direct display of measured sensor values			
Clock	Real-time clock with date			
Module slots	6			
Electrical connection	Plug-in connectors			
Recommended cable Solid H05(07) V-U Flexible H05(07) V-K With wire end ferrule With plastic collar ferrule	Shielded cable, clamping range 0.2 up to 1.5 mm ² 0.2 up to 1.5 mm ² 0.2 up to 1.5 mm ² 0.2 up to 1.5 mm ²			



Technical data - Mainboard				
Electrical data				
Power supply ("SUPPLY")	12-36 V DC, filtered and regulated			
Power consumption (of multiCELL device - with- out additional modules and outputs not connected)	Max. 1.5 VA			
Power charges ("PWR OUT")	12-36 V DC, max 1.8 A			
Digital inputs DI1, DI2	Voltage: 5-36 V DC, input impedance 3 k Ω Frequency: 0.5 up to 2500 Hz Galvanic insulation Protected against reversed polarity of DC and voltage peak			
Digital outputs DO1, DO2 Transistor	Can be wired as PNP or NPN, galvanic insulation, protected against short circuit, max. 36 V DC, max. 700 mA if only one transistor output is used, 1 A max. in total if both transistor outputs are used			
Frequency Analog output AO1, AO2	max. 2000 Hz 4 20 mA, can be wired as sourcing or sinking, galvanic insulation, protected against reversed polarity of DC, max. loop impedance: 1100 Ω at 36 V DC, 610 Ω at 24 V DC, 100 Ω at 12 V DC			
Memory card Type Capacity File system 'SDHC cards can not be used	SD (Secure Digital)* max. 2 GB FAT16			

Materials view



*SDHC cards can not be used

Additional modules

3 different types of modules are available and can be inserted into any of the 6 slots (preconfigured at the factory)

- input pH/ORP and Pt100/Pt1000 modules
- input conductivity and Pt100/Pt1000 modules
- output module : 2 transistor outputs and 2 analog 4 ... 20 mA outputs

Technical data - pH/ORP module			
Power consumption	0.1 VA		
pH/ORP input	simultaneous pH and ORP measurement with input for electrochemical pH/ORP		
Temperature input	Pt100 / Pt1000, 2 or 3 wires		
pH measurement			
Measuring range	-2.016 pH or -600 +600 mV		
Resolution	0.01 pH or 0.1 mV		
Accuracy	±0.02 pH or 1 mV		
ORP measurement			
Measuring range	-2000+2000 mV		
Resolution	0.1 mV		
Accuracy	± 1 mV		
Temperature			
measurement			
Measuring range	-25 to +130°C (-20 to 266°F)		
Resolution	0.1°C (0.18°F)		
Accuracy	± 1°C (1.8°F)		

Technical data - conductivity module			
Power consumption	0.25 VA		
Conductivity input	Operation with 2- or 4-pole-technology		
	sensors		
Temperature input	Pt100 / Pt1000, 2 or 3 wires		
Conductivity/Resis-			
tivity measurement			
Conductivity			
Measuring range	0 μS/cm 2 S/cm		
Resolution	1 nS/cm		
Accuracy (without probe)	< 0.5% of measured value		
Resistivity			
Measuring range	0.5 Ω/cm 2 MΩ/cm		
Resolution	0.1 Ω/cm		
Accuracy (without probe)	< 0.5% of measured value		
Temperature			
measurement			
Measuring range	-40 to +200°C (-40 to 392°F)		
Resolution	0.1°C (0.18°F)		
Accuracy	± 1°C (1.8°F)		



Technical data - output module			
Power consumption Max. 0.1 VA			
Digital outputs DO1, DO2 Transistor	Can be wired as PNP or NPN, galvanic insulation, pro- tected against short circuit, max. 36 V DC, max. 700 mA, 1 A max. per transistor if the 2 transistor outputs are wired		
Frequency	max. 2000 Hz		
Analog output AO1, AO2	4 20 mA, can be wired as sourcing or sinking, galvan- ic insulation, protected against reversed polarity of DC, max. loop impedance: 1100 Ω at 36 V DC, 610 Ω at 24 V DC, 100 Ω at 12 V DC		

Environment conditions and Standards - Mainboard, pH/ORP, conductivity, output modules					
Ambient temperature Operation	-10 to +60°C (14 to 140%) - limited at 0 to 60°C (32 to 140%) if memory card is used	Protection class	IP65 (panel-mounted, cabinet closed) IP20 (panel-mounted, inside the cabinet) NEMA 4X (panel-mounted, in front of the closed cabinet)		
Storage	-20 to +60°C (-4 to 140°F)	Standard and			
Relative humidity	< 85%, without condensation	directives CE			
		EMC	EN 61000-6-2, EN 61000-6-3		
		Vibration / Shock	EN 60068-2-6 / EN 60068-2-27		
		Approvals			
		UL-Recognized for			
		US and Canada Stus	61010-1 + CAN/CSA-C22 No.61010-1		

Principle of operation

The transmitter/controller is given by the internal module based structure capable to handle different types of sensors and selectively execute operations on the measurement values. From simple measurement and standard signal output and assignment of integrated mathematical formulas for selectable values up to control tasks all that can run in parallel.

The modules for signals and functions can be easily connected to eachother and with setting individual parameters all the functionality can be adapted to the actual process conditions. A 12-36 V DC power supply is sufficient to have the device running.

The base unit is a panel mount version and handles analog and digital signal outputs, digital inputs and the front is supplied by a backlit graphical display. Up to six slots are available, which depending on the applications, can be occupied with modules for pH/O.R.P., conductivity as well a module with additional analog and digital outputs. There is no need for a separate 4...20 mA transmitter: the pH, conductivity modules accept raw signals from sensors.

Though highly functional the multiCELL can be operated easily and intuitively. The base for this is the large graphical display and the dynamically assigned function keys. Clearly arranged menu and module structures allow easy configuration and setting of parameters and offer a high transparency for the functions in use. Four user views can be configured by the operator. This allows the user to design a view himself displaying a value arrangement which he likes to see simultaneously and this can be available 4 times and independent from eachother.

For data collection and storage e.g. of measurement values, calibration parameters and as well the complete device database with restore functionality there is an optional data logger available which uses the memory card if inserted in the card slot.

Construction

The mainboard enables:

- Connection to the transmitter/controller power supply
- to power another device
- to dispose of 2 digital inputs (DI), 2 analog (AO) and 2 digital (DO) outputs



Memory card slot :

For upload and download of parameter settingsSoftware updates

Simple operation: insert the memory card into the small slot on the rear of the device.

Additional module slots (up to 6) to choose among:

- module for pH/O.R.P. sensor and/or
- temperature sensor
- module for conductivity sensor and/or temperature sensor
- module for 2 analog and 2 digital outputs



Display and dynamic soft keys



Process diagram





Control functions

The transmitter/controller allows to allocate each sensor signal to a function (such as dosage, for example) fully configurable by the user. According to the model the following functions are offered as standard or as option

Functions	Availability	Formula	Example for usage
Arithmetic	Basis for all models	A+B, A-B, A/B	arithmetic operation between 2 values with same units. A or B can be a result of another function
PASS	Basis for all models	<mark>≜</mark> x 100%	calculates a flow ratio between 2 values. e.g: reverse osmosis
REJECT	Basis for all models	(1 - <mark>A</mark>) x 100%	calculates a reject ratio between 2 values. e.g: reverse osmosis
DEVIAT	Basis for all models	(<mark>A</mark> - 1) x 100%	calculates a deviation ratio between 2 values.
PROP	Basis for all models	100%- 0% scal- scal+ value	calculates an output in proportion to a scaled input
ON/OFF	Basis for all models	On/Off control loop	for any type of input
Flow rate measurement	As base for model item no. 560205, 560213, for others as option		allows both digital inputs to be used as frequency inputs for flow measurement (in standard for base unit) or in parallel to analytical modules
PID	As option	Continuous control loop	for any type of input and with internal or external setpoint
Time dosing	As option		e.g. for cooling tower application. Dosing of 1 or 2 biocides in the circuits, at fixed time intervals or by defining dosing during one week, with 2 dosings per day. Can be connect- ed to an ON/OFF conductivity function for prebleed.
Special Chemical batch (Volume dosing)	As option		specifically for cooling tower application. A defined volume of water is counted, then an actuator is energized during a defined time to add a chemical and the water volume being counted is resetted.
Concentration	As option		the concentration curves of NaCl, H_2SO_4 , HNO ₃ , NaOH, Hcl are implemented for use in complete concentration range and not only in low concentration.
Data logger on memory card	As option		up to 16 values can be stored at a defined time interval.



Menu structure



p. 6/9



Dimensions [mm]



Ordering chart for multiCELL transmitter/controller Type 8619

			Inputs		Outpu	ts		
Description	Power supply	Digital (DI) (On/Off or frequency)	number and type of sensor raw signal	Pt100/Pt1000	Transistor (po) (PWM or PFM or On/ Off or pulse)	Analog 4-20 mA	UL Approvals	Item no.
BASE unit							No	560 205
(Mainboard)	12-36 V DC	2	-	-	2	2	UL-Recognized	560 213
							No	560 200
pH/ORP (Mainboard + 1 pH/ORP module)	12-36 V DC	2	1 (pH/ORP)	1	2	2	UL-Recognized	560 208
pH/ORP							No	560 202
(Mainboard + 2 pH/ORP modules + 1 output module)	12-36 V DC	2	2 (pH/ORP)	2	4	4	CRU-Recognized	560 210
CONDUCTIVITY							No	560 201
(Mainboard + 1 conductivity module)	12-36 V DC	2	1 (Cond.)	1	2	2	UL-Recognized	560 209
CONDUCTIVITY							No	560 203
(Mainboard + 2 conductivity modules + 1 output module)	12-36 V DC	2	2 (Cond.)	2	4	4	UL-Recognized	560 211
pH/ORP and CONDUCTIVITY			1 (11(000))				No	560 204
(Mainboard + 1 pH/ORP module + 1 conductivity module + 1 output module)	12-36 V DC	2	1 (pH/ORP) + 1 (Cond.)	2	4	4	UL-Recognized	560 212

Note regarding the ordering of above mentioned multiCELL transmitter/controller:

The above items are equipped of arithmetic, PASS, REJECT, DEVIAT, PROP, ON/OFF functions in standard (see p.4 Control functions). In the BASE unit the **Flow measurement function** is also a standard function, the other functions are available as option.

Please also use the "request for quotation" form on page 9 go to page for ordering a device with additional options.



Ordering chart for additional software functions for Type 8619

Use the following order codes only in case you already own a 8619 and you like to add one or more of the given functions to your device.

Please don't forget to jot down on the order the Item no. of your 8619 multiCELL transmitter/controller and its serial number (see the device label).

Function	Description	Item no.
PID control	with each hardware version	561 836
Memory card (Data Logger)	with each hardware version	561 837
Chemical dosing (e.g. cooling tower)	with each hardware version	561 838
Flow measurement	with analytical hardware version	561 839
Concentration measurement of selected fluids	with conductivity hardware version	561 840

Interconnection possibilities with other Bürkert devices



When you click on the orange box "More info." below, you will come to our website for the resp. product where you can download the data sheet.

burkert

Note

multiCELL Transmitter/controller Type 8619 - request for quotation

Please fill in and send to your local Bürkert Sales Centre* with your inquiry or order.

Please fill in and send to your local Bürk	You can fill out the fields directly in the PDF file before printing out the form.	
Company:	Contact person:	before printing
Customer No.:	Department:	Out with
Address:	Tel. / Fax.:	
Postcode / Town:	E-mail:	

multiCELL Transmitter/controller 8619				
	Quantity:	Desired deliver	y date:	
Hardware:	Mainboard (without flow function)			
Slot M1	pH/ORP + temperature module	conductivity + temperature module	output module	
Slot M2	pH/ORP + temperature module	conductivity + temperature module	output module	
Slot M3	pH/ORP + temperature module	conductivity + temperature module	output module	
Slot M4	pH/ORP + temperature module	conductivity + temperature module	output module	
Slot M5	pH/ORP + temperature module	conductivity + temperature module	output module	
Slot M6	pH/ORP + temperature module	conductivity + temperature module	output module	
Software:	_			
	PID			
	Data logger			
	Chemical dosing (e.g. Cooling Tower) +	special batch		
	Flow measurement			
	Concentration Measurement for selected fluids (only if one of the slot equipped with conductivity module)			

To find your nearest Bürkert facility, click on the orange box ightarrow

www.burkert.com

In case of special application conditions, please consult for advice.

Subject to alteration. © Christian Bürkert GmbH & Co. KG

1010/1_EU-en_00895144